

Bass Cabinet Configurations

About this document

This document outlines allowed cabinet configurations on TC bass amps and cabs.

The guide is subject to change without notice, and will be updated as new items are added to the TC bass range.

Amp head	RS cabinet configurations	BC cabinet configurations	Non TC cabinets
RH750 / RH450 / CL450 / Staccato'51			
	Any combination of three RS cabinets – <i>Example A: 2x RS212 + 1x RS410</i> <i>Example B: 3x RS112</i>	Any combination of three BC210's or BC212's <i>Example: 1x BC212 + 2x BC210</i>	Min. Nominal 4 ohm impedance load
		BC210 or 212 + BC410	
BH500			
	Any combination of three RS cabinets – <i>Example A: 2x RS212 + 1x RS410</i> <i>Example B: 3x RS112</i>	Any combination of three BC210's or BC212's <i>Example: 1x BC212 + 2x BC210</i>	Min. Nominal 4 ohm impedance load
		BC210 or 212 + BC410	
		2x BC410	
Blacksmith			
4 ohm mode	Any two RS cabinets	BC210 or 212 + BC210 or 212	Min. Nominal 4 ohm impedance load
2 ohm mode	Any four RS cabinets	Any combination of four BC210 or BC212's	Min. Nominal 2 ohm impedance load
		Any combination of two BC210 or BC212's + BC410	
		2x BC410	

TC Cabinet Impedance loads			
Cabinet	Impedance load	Cabinet	Impedance load
RS112	8 ohm	BC210	8 ohm
RS210	8 ohm	BC212	8 ohm
RS212	8 ohm	BC410	4 ohm
RS410	8 ohm		